



GENERAL NOTES:

1. DISCONNECT PLACED AT OR NEAR A CPU TRANSFORMER OR POWER PEDESTAL.
2. 1" CONDUIT FROM THE DISCONNECT TO FIRST J-BOX.
3. 1" CONDUITS WILL BE REQUIRED FROM J-BOX TO J-BOX FOR DAISY CHAINED CIRCUITS.
4. TYPE 1 J-BOX WILL BE PLACED AT EACH POLE WITHIN FOUR FEET.
5. GROUND ROD NEEDS TO BE INSTALLED IN EACH J-BOX. ALL METAL POLES SHALL BE GROUNDED.
6. 1" PVC FLEX SHALL BE USED TO GO FROM J-BOX TO LIGHT POLE.
7. EACH HOT LEG NEEDS TO BE FUSED AT THE BASE OF EACH POLE.
8. ALL WIRES IN J-BOX SHALL BE TERMINATED USING (POLARIS SALES CO. INC IPL4-4, 4-14 AWG CU9AL WIRE CONNECTOR) OR EQUIVALENT, OR COMPRESSION CONNECTIONS.
9. LIGHT POLES NEED TO BE INSTALLED USING OUR APPROVED STEEL ANCHOR BASES, UNLESS THE POLE IS A DIRECT BURY STYLE.

I:\CITYAPPS\AUTOCAD\STD_DETAILS\DRAWING_FILES\T21-18D.DWG



DIRECT FEED LIGHTING (NEIGHBORHOODS)

CITY OF VANCOUVER
DEPARTMENT OF PUBLIC WORKS
TRANSPORTATION DIVISION

DRAWN BY	APPROVED BY	APPROVAL DATE
CDC		2/21
REVISION	APPROVED BY	APPROVAL DATE
4		3/24

STD. PLAN NO.
T21-18D